

## High Power Single and Dual Directional Couplers

Single Directional [View Dual Directional](#)

Frequency Range (MHz)		Coupling (dB)	Coupling Flatness (dB) max.	Insertion Loss (dB) max.	Directivity (dB) min.	VSWR In/Out max.	Input Power (watts) max.	Connector Type	P/N
Min	Max								
1500	3000	35 ± 1	±1.00	0.20	20	1.20:1	600	N	<a href="#">C35-29-481/9N</a> <input type="button" value="Add to RFQ"/>
2000	4000	35 ± 1	±1.00	0.20	20	1.20:1	600	N	<a href="#">C35-30-481/9N</a> <input type="button" value="Add to RFQ"/>
1000	8000	35 ± 1	±1.00	0.25	15	1.40:1	500	N	<a href="#">C35-27-481/9N</a> <input type="button" value="Add to RFQ"/>
1000	10000	35 ± 1	±1.00	0.30	12	1.40:1	500	N	<a href="#">C35-28-481/9N</a> <input type="button" value="Add to RFQ"/>



Outline 481/9N  
3.83" x 1.10" x 0.80"

Name: C35-29-481/9N  
 Frequency Range: 1500-3000 MHz  
 Coupling: 35 ± 1 dB  
 Coupling Flatness: ±1.00 dB max.  
 Insertion Loss: 0.20 dB max.  
 Directivity: 20 dB min.  
 VSWR In/Out: 1.20:1 max.  
 Input Power: 600 watts max.  
 Connector Type: N

更多信息，请联系我们：

地址：上海市普陀区祁连山南路 2888 号耀光中环国际 A 座 9H 室

Tel: 021-5291 8556, Fax: 021-6260 7783

www.fulai-elec.com

Email: sales@fulai-elec.com

## Dual Directional

Frequency Range (MHz)		Coupling (dB)	Coupling Flatness (dB) max.	Insertion Loss (dB) max.	Directivity (dB) min.	VSWR In/Out max.	Input Power (watts) max.	Connector Type	P/N
Min	Max								
2.0	32	30 ± 1	±0.25	0.10	25	1.10:1	100	N	<a href="#">C30-104-481/2N</a> <input type="button" value="Add to RFQ"/>
2.0	32	30 ± 1	±0.25	0.10	25	1.10:1	100	SMA	<a href="#">C30-104-481/2S</a> <input type="button" value="Add to RFQ"/>
2.0	32	50 ± 1	±0.25	0.06	25	1.10:1	2500	N	<a href="#">C50-101-481/1N</a> <input type="button" value="Add to RFQ"/>
0.5	50	50 ± 1	±0.50	0.10	20	1.10:1	2000	N	<a href="#">C50-100-481/1N</a> <input type="button" value="Add to RFQ"/>
0.5	100	30 ± 1	±0.50	0.30	25	1.15:1	200	N	<a href="#">C30-102-481/2N</a> <input type="button" value="Add to RFQ"/>
0.5	100	30 ± 1	±0.50	0.30	25	1.15:1	200	SMA	<a href="#">C30-102-481/2S</a> <input type="button" value="Add to RFQ"/>
0.5	100	40 ± 1	±0.30	0.20	20	1.15:1	200	N	<a href="#">C40-103-481/2N</a> <input type="button" value="Add to RFQ"/>
0.5	100	40 ± 1	±0.30	0.20	20	1.15:1	200	SMA	<a href="#">C40-103-481/2S</a> <input type="button" value="Add to RFQ"/>
1.0	100	50 ± 1	±1.00	0.20	20	1.20:1	500	N	<a href="#">C50-109-481/1N</a> <input type="button" value="Add to RFQ"/>
1.0	100	40 ± 1	±1.00	0.20	20	1.20:1	500	N	<a href="#">C40-110-481/1N</a> <input type="button" value="Add to RFQ"/>
20	200	50 ± 1	±0.75	0.20	20	1.15:1	500	N	<a href="#">C50-108-481/4N</a> <input type="button" value="Add to RFQ"/>
0.1	250	40 ± 1	±0.50	0.40	20	1.20:1	250	N	<a href="#">C40-111-481/5N</a> <input type="button" value="Add to RFQ"/>
20	400	30 ± 1	±0.50	0.30	20	1.15:1	50	N	<a href="#">C30-107-481/3N</a> <input type="button" value="Add to RFQ"/>
20	400	30 ± 1	±0.50	0.30	20	1.15:1	50	SMA	<a href="#">C30-107-481/3S</a> <input type="button" value="Add to RFQ"/>
0.1	500	40 ± 1	±0.50	0.50	20	1.20:1	200	N	<a href="#">C40-112-481/5N</a> <input type="button" value="Add to RFQ"/>
50	500	40 ± 1	±1.0	0.20	20	1.15:1	500	N	<a href="#">C40-21-481/4N</a> <input type="button" value="Add to RFQ"/>
50	500	50 ± 1	±1.0	0.20	20	1.15:1	500	N	<a href="#">C50-21-481/4N</a> <input type="button" value="Add to RFQ"/>
100	500	40 ± 1	±0.50	0.20	20	1.15:1	500	N	<a href="#">C40-105-481/4N</a> <input type="button" value="Add to RFQ"/>
80	1000	40 ± 1	±1.00	0.30	20	1.20:1	1000	N	<a href="#">C40-27-481/4N</a> <input type="button" value="Add to RFQ"/>
80	1000	50 ± 1	±1.00	0.30	20	1.20:1	1000	N	<a href="#">C50-27-481/4N</a> <input type="button" value="Add to RFQ"/>
80	1000	40 ± 1	±1.00	0.30	20	1.20:1	1500	N	<a href="#">C40-31-481/4N</a> <input type="button" value="Add to RFQ"/>
80	1000	50 ± 1	±1.00	0.30	20	1.20:1	1500	N	<a href="#">C50-31-481/4N</a> <input type="button" value="Add to RFQ"/>
100	1000	40 ± 1	±1.00	0.40	20	1.20:1	500	N	<a href="#">C40-20-481/4N</a> <input type="button" value="Add to RFQ"/>
100	1000	50 ± 1	±1.00	0.40	20	1.20:1	500	N	<a href="#">C50-20-481/4N</a> <input type="button" value="Add to RFQ"/>
100	1000	40 ± 1	±1.00	0.30	20	1.20:1	1000	N	<a href="#">C40-25-481/4N</a> <input type="button" value="Add to RFQ"/>
100	1000	50 ± 1	±1.00	0.30	20	1.20:1	1000	N	<a href="#">C50-26-481/4N</a> <input type="button" value="Add to RFQ"/>
500	1000	50 ± 1	±0.50	0.20	20	1.15:1	500	N	<a href="#">C50-106-481/4N</a> <input type="button" value="Add to RFQ"/>

更多信息，请联系我们：

地址：上海市普陀区祁连山南路 2888 号耀光中环国际 A 座 9H 室

Tel: 021-5291 8556, Fax: 021-6260 7783

www.fulai-elec.com

Email: sales@fulai-elec.com